

## C&D VRLA Battery Replacements for Power Battery Models

Manufacturer	Model Number	Ampere Rate to 1.75 vpc @ 77F/25C			Length in(mm)	Width in(mm)	Height in(mm)	Weight lbs(kgs)	Terminals
		1 Hr	4 Hr	8 Hr					

### Telecom Batteries (12 V & 6 V blocks)

#### Top Terminal

If you have	Power Battery	TL-1230	20.30	6.74	3.65	7.71(196)	5.2(132)	7.2(183)	26.7(12.0)	L-Type
Replace with	C&D	TEL12-30	22.10	7.15	3.80	7.77(197)	5.19(132)	6.80(173)	27.3(12.4)	10-32 Insert
If you have	Power Battery	TL-1250	31.40	10.40	5.65	8.60(219)	5.4(137)	8.20(208)	35.3(16.0)	Insert
Replace with	C&D	TEL12-45	31.50	10.25	5.69	8.99(229)	5.48(139)	8.07(205)	40.6(18.4)	1/4" Insert
If you have	Power Battery	TL-1270	47.60	15.80	8.58	10.2(259)	6.7(169)	9.0(229)	60.6(27.5)	Insert
Replace with	C&D	TEL12-70	46.80	15.55	8.64	10.26(261)	6.83(173)	8.01(204)	55.8(25.3)	1/4" Insert
If you have	Power Battery	TL-1280	57.10	19.00	10.30	12.0(305)	6.7(169)	9.1(231)	71.9(32.7)	Insert
Replace with	C&D	TEL12-80	53.80	17.50	9.88	12.04(306)	6.83(173)	8.06(205)	66.6(30.2)	1/4" Insert
If you have	Power Battery	TL-1295	66.70	22.10	12.00	13.5(343)	6.8(173)	8.5(215)	80.6(36.7)	Insert
Replace with	C&D	TEL12-90	60.00	19.70	10.95	13.42(341)	6.80(173)	8.52(216)	74.5 (33.8)	1/4" Insert
If you have	Power Battery	TL-12120	81.30	27.00	14.70	13.5(343)	6.8(173)	10.8(273)	99.4(45.2)	Insert
Replace with	C&D	TEL12-125	87.50	28.40	15.75	13.57(345)	6.80(173)	10.93(278)	102.3(46.4)	1/4" Insert
If you have	Power Battery	TL-6195	132.00	43.60	24.10	10.7(272)	7.4(187)	10.9(279)	81.5(37)	Insert
Replace with	C&D	TEL6-180 (6V)	120.00	39.20	21.94	12.63(321)	6.97(177)	8.94(227)	74.5(33.8)	1/4" Insert

#### Front Terminal

If you have	Power Battery	CSL-1280/FT-1290	57.50	19.10	11.20	15.25(387)	4.13(105)	11.81(300)	68.0(31.0)	1/4" Insert
Replace with	C&D	TEL12-105FN5G	72.90	23.50	13.00	16.1(410)	4.1(106)	11.3(287)	72(32.8)	M8 Insert
If you have	Power Battery	CSL-12100/FT-12100	68.70	22.70	12.50	21.0(534)	4.28(109)	9.63(245)	78(35.4)	1/4" Insert
Replace with	C&D	TEL12-115FNG	71.30	23.70	13.50	20.1(511)	4.3(110)	9.3(235)	80(36)	M6 Insert
If you have	Power Battery	FT-12160	105.00	35.02	19.38	21.96(558)	4.86(123)	11.81(300)	128(58.2)	1/4" Insert
Replace with	C&D	TEL12-160F	107.10	35.40	19.70	22.01(559)	4.95(126)	11.14(283)	115(53)	1/4" Insert
If you have	Power Battery	FT-12180	123.90	38.80	21.90	21.96(558)	4.86(123)	12.6(320)	136(61.6)	1/4" Insert
Replace with	C&D	TEL12-180F	123.1	40.8	22.6	22.01(559)	4.95(126)	12.60(320)	131(60)	1/4" Insert