

C&D VRLA Battery Replacements for Power Battery Models

Manufacturer	Model Number	Watts Per Cell Rate to 1.67 epv @ 77F/25C			Length in(mm)	Width in(mm)	Height in(mm)	Weight lbs(kgs)	Terminals
		5 min	10 min	15 min					

UPS High Rate Batteries (12 V & 6 V blocks)

If you have	Power Battery	PRC/TC-1225	115	88	71	6.50(165)	6.81(173)	4.94(125)	21.5(9.75)	Flag
Replace with	C&D	UPS12-100MR	172	117	91	6.54(166)	5.17(131)	6.86(162)	21.0(10)	S.Flag
If you have	Power Battery	PRC/TC-1235L	269	173	131	7.71(196)	5.18(132)	7.19(183)	26.7(12.1)	L-Type
Replace with	C&D	UPS12-150MR	288	192	148	7.76(197)	5.19(132)	6.80(173)	27.3(12.4)	10-32 Insert
If you have	Power Battery	PRC/TC-1250S	298	225	175	8.60(218)	5.5(140)	9.00(229)	35.3(16.0)	1/4" Stud
Or	Power Battery	PRC/TC-1255S	388	258	206	8.60(218)	5.5(140)	9.00(229)	37.0(16.8)	1/4" Stud
Replace with	C&D	UPS12-210MR	376	257	206	9.0(229)	5.48(139)	8.07(205)	40.0(18.0)	1/4" Insert
If you have	Power Battery	PRC/TC-1290S	508	365	284	10.2(259)	6.67(169)	8.25(225)	60.6(27.5)	1/4" Stud
Replace with	C&D	UPS12-300MR	550	382	300	10.27(261)	6.83(173)	8.01(204)	58.4(26.5)	1/4" Insert
If you have	Power Battery	PRC/TC-12100S	543	409	318	12.0(305)	6.68(170)	8.85(225)	67.2(30.5)	1/4" Stud
Replace with	C&D	UPS12-350MR	620	440	350	12.04(306)	6.83(173)	8.06(205)	67.4(30.5)	1/4" Insert
If you have	Power Battery	PRC/TC-12120S	753	512	400	13.5(344)	6.76(172)	9.25(235)	78.5(35.6)	1/4" Stud
Replace with	C&D	UPS12-400MR	720	505	400	13.42(341)	6.80(173)	8.52(216)	75.8 (34.4)	1/4" Insert
If you have	Power Battery	PRC/TC-12150C	913	650	505	13.5(344)	6.76(172)	10.87(276)	103.5(46.9)	1/4" Insert
Replace with	C&D	UPS 490MRLP	788	608	488	13.42(341)	6.80(173)	8.52(216)	83.0(38.0)	1/4" Insert
Or	C&D	UPS12-490MR	773	590	488	13.57(345)	6.80(173)	10.93(278)	100(45.0)	1/4" Insert
If you have	Power Battery	PRC/TC-12150C	913	650	505	13.5(344)	6.76(172)	10.87(276)	103.5(46.9)	1/4" Insert
Or	Power Battery	TC-12160C	928	700	560	13.5(344)	6.76(172)	10.87(276)	110.0(49.8)	1/4" Insert
Replace with	C&D	UPS12-540MR	868	654	537	13.57(345)	6.80(173)	10.93(278)	100(45.0)	1/4" Insert
If you have	Power Battery	PRC/TC-6225S	614	466	377	10.7(272)	7.38(187)	11.6(295)	79.0(35.9)	1/4" Insert
Replace with	C&D	UPS6-620 (6V)	940	750	620	12.63(321)	6.97(177)	8.94(227)	72.0(33.0)	1/4" Insert
If you have	Power Battery	SLF-12105	546	409	318	21.0(534)	4.28(109)	9.63(245)	74.0(33.6)	1/4" Insert
Or	Power Battery	SLF-12120	633	477	371	21.0(534)	4.28(109)	9.63(245)	84.0(38.2)	1/4" Insert
Or	Power Battery	SLF-12205	1307	944	742	21.1(536)	8.46(215)	10.1(256)	152(69.0)	5/16" Insert
Or	Power Battery	SLF-12250	1325	1047	838	21.1(536)	8.46(215)	10.1(256)	162(73.4)	5/16" Insert
Replace with	C&D	UPS12-700F	1059	853	700	20.16(512.17)	4.86(123.39)	12.19(309.55)	131(60)	1/4" Insert

* System will have to be sized to assure proper fit. Front access batteries are not a Fit replacement and will likely require new cabinets/racks.